

## NEW COMPUTER TECHNOLOGY SYSTEMS (NCTS) LIMITED COMPANY

新计算机科技系统 (NCTS) 有限公司

深圳市龙岗区布吉诚信华庭2栋6B

[www.ncts.co](http://www.ncts.co)

### COAXIAL CABLE NCTS-RG59+2C WITH POWER CABLE

RG59 Coaxial with Power cable allows installers to run both the video and power to security cameras using a single cable run. It also offers maximum protection from electromagnetic interference as its heavily shielded so that it has the durability to handle long-term installation over long-distance runs.

#### SPECIFICATIONS:

Conductor	BC/Copper Clad Steel(CCS 23%)
Conductor Dia.	20AWG
Insulation	FPE
Insulation Dia.	3.66 mm
Shielding	Aluminium Foil
Braid Shielding	CCA/AL
Braid Coverage Area (%)	60%-100%
Jacket	PVC
Jacket Dia	6.0±0.2mm
Power Cable	
Conductor Material	BC/CCA
Insulation	PVC
Conductor Size	2x0.5mm / 2x0.75mm /2x1.5mm
Jacket	PVC
Jacket Dia.	4.0mm
Colors	Optional
Length& Package	100/200 with PE film Packing
	305m/500m with wooden reel packing

#### ELECTRICAL CHARACTERISTICS FOR RG59:

Max.DC Inner Conductor Resistance	320 Ohm/km
Max.DC Outer Conductor Resistance	45 Ohm/km
Characteristic Impedance	75 ±3Ω
Nom. Mutual Capacitance	68 pf/m
Velocity Radio	66%
Dielectric Strength	1000 vac
Min. Insulation Resistance	0000 MOhms*km
Operating Voltage	300V
Coaxial cable signal (Attenuation)Loss per 100 ft	
Frequency(MHZ)	Max.Attenuation(db/100ft)
1 MHZ	0.4db
10 MHZ	1.4db
50MHZ	3.3db
100 MHZ	4.9db
200 MHZ	7.3db
400MHZ	11.2db
700 MHZ	16.9db
900 MHZ	20.1db
1000MHz	21.5db

#### ELECTRICAL CHARACTERISTICS FOR POWER CABLE:

Type	Max.DC Inner Conductor Resistance
2x0.5mm	36 Ohm/km
2x0.75mm	24 Ohm/km
2x1.5mm	14 Ohm/km